

TECHNICAL DATA

Fluke VPS410-II-R ScopeMeter® Voltage Probe Set



Key features

- Ideal for industrial and electronics applications
- Double insulated, CAT III 1000V / CAT IV 600V rated
- 10:1 voltage ratio and 500 MHz bandwidth
- Available in red, blue, grey, and green

Product overview: Fluke VPS410-II-R ScopeMeter® Voltage Probe Set

Use the Fluke VPS410-II-R (Red) Voltage Probe with the [Fluke 190 Series III](#) and Series II Portable Oscilloscopes or with the [MDA-500 Series Motor Drive Analyzers](#). These double insulated probes offer a 10:1 voltage ratio, and 500 MHz bandwidth making them ideal for industrial, electrical and electronics testing. For smaller size electronic applications consider Fluke [VPS510-R Compact Voltage Probes](#). For test on heavy equipment such as motors and drives, consider the larger and ruggedized Fluke [VPS421 Series High Voltage Probes](#).

Specifications: Fluke VPS410-II-R ScopeMeter® Voltage Probe Set

Specifications*

Attenuation	10:1
Bandwidth	500 MHz
Max. input voltage	CAT III 1000V / CAT IV 600V
Max. voltage to ground	CAT III 1000V / CAT IV 600V
Input Resistance	10 MΩ
Input Capacitance	11.5 ± 1 pF
Compensation range	10...25 pF
Cable Length	1.2 m (3.9 ft)
Safety	IEC / EN 61010-031 UL 61010-031 CSA C22.2 No. 1010.2.031
Max. Altitude	3000 m
Pollution Degree	2
Protection Class	II (double insulation)

*Specification of probe is valid only when used with Fluke ScopeMeter 190-xxx models and MDA-500 series.

Ordering information



Fluke VPS410-II-R

Industrial Voltage Probe-set, red, 10:1, 500 MHz

Part#: 4276928

UPC#: 095969655613

Includes:

- (1) Red voltage probe
 - (1) Black hook clip for probe tip
 - (1) Black ground lead with mini alligator clip
 - (1) Ground spring for probe tip (CAT II 30 V max.)
 - (1) Insulation sleeve for probe tip
-

Fluke. *Keeping your world up and running.®*

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:
In the U.S.A. (800) 443-5853
In Canada (800) 36-FLUKE
From other countries +1 (425) 446-5500
www.fluke.com

©2026 Fluke Corporation.
Specifications subject to change without notice.
08/2026

**Modification of this document is not permitted
without written permission from Fluke
Corporation.**